

	RW10-I-20F / 100	RW10-I-20F / 200
□□		
Max. □□ □□ V	20	20
□□ □□ Hz	50/60	50/60
□□ □□ □□ □□	100	200
ASYM		
□□ □□ □□ □□	12000	12000
□□ □□ □□		
□□□ □□□ □□ V	115	115
1 □□ □□□ □□ V	□□ 40	40
	□□ 34	34
□□□□□ □□ □□ mm	235	235